







Now, the CD music has been ripped and saved in USB flash drive, you can just save it for backup; Or you can play it at PC, Home Theater, Portable Speaker, Cat...etc.



Play on mobile phone, let's see how to do:

1, Set your mobile phone's Wi-Fi connect to CDRip(password: 12345678)



IN IOS:

2, Download an App – FileExplorer (there are other Apps can use, such as VLC, or anyone can support SAMBA), here we just example FileExplorer:

3, Run FileExplorer, click "+", then choose "Windows"



4, Choose CDRIP, Connect as "Guest":

New Connection	Save
Path	Optional
Port	445
Show Hidden Files	\bigcirc
Show Admin Shares	\bigcirc
Support DFS	\bigcirc
CONNECT AS	
User Name	Optional
Password	Optional
If you try to access network share please input 'Domain\User' or 'Us User Name text field.	e in domain, er@Domain' in
NETWORK NEIGHBORHOOD	
CDRIP 43.44.45.46	
/	

5, Enter Media1—USB—CDrip—CD1(or CD2, CD3 ...)



< USB	media1			Edit	
Name↑	Date	Size	Туре		
2019	ip 9/7/16, 16:4	40:50		0 0 0	
Sys 2016	tem Volur 5/7/19, 16:0	me Inforr 08:24	mation	0 0 0	
	2 Fol	ders, 0	File		



1 Folder, 0 File

6, Now you can press one of the music lists to play:

< CDrip CD1	Edit
Name↑ Date Size Type	
01.track1.wav 2019/7/5, 15:07:34 39.11 MB	0 0 0
02.track2.wav 2019/7/5, 15:09:31 37.59 MB	0 0 0
03.track3.wav 2019/7/5, 15:11:44 47.88 MB	0 0 0
04.track4.wav 2019/7/5, 15:13:14 33.84 MB	0 0 0
05.track5.wav 2019/7/5, 15:14:40 32.29 MB	0 0 0
06.track6.wav 2019/7/5, 15:16:37 47.13 MB	0 0 0
Q +	₽

7, Or press:



То



You can download, or rename, or open with other player, or other functions.

IN ANDROID:

There are also many App can be use, here we example with ES File Explorer:

After download, run it, press 🧮



Choose Network—LAN:



Press " Scan",



When you see the result "CDRIP", stop scan:

E 🔒 LAN X	:
LAN	New
CDRIP 43.44.45.46	

Then enter Drip—USB—Media1—CDrip—CD1(Or CD2, CD3 ...)

	=	A	LAN			Q	:
3	>	media1	>	CDrip	>	CD1	
	12 52	2.track12.w .38 MB	/av	-rw		7/5/201	9
(11	.track11.w	av	-04		7/5/201	

You can choose one to rename or edit:

1/12	Select All	↔ Select Interval	↓ Cancel
) > media1 >	CDrip	> CD	l.
12.track12.wav 52.38 MB	-rw	7/5	/2019 🕑
11.track11.wav 58.36 MB	-rw	7/5	/2019
10.track10.wav 33.61 MB	-rw	7/5	/2019
09.track09.wav 48.12 MB	-rw	7/5/	2019
08.track8.wav 43.60 MB	-rw	7/5/	2019
07.track7.wav 35.55 MB	-rw	7/5/	2019
06.track6.wav 47.13 MB	-rw	7/5	/2019
05.track5.wav 32.29 MB	-rw	7/5/	2019
04.track4.wav 33.84 MB	-rw	7/5	/2019
03.track3.wav 47.88 MB	-rw	7/5	/2019
02.track2.wav 37.59 MB	-nw	7/5/	2019
Copy Cut	Delete] Rename	More

Or, press more to play, or move, or other perpose:



Finally, we can enjoy it now.....

Oh~, one more thing:

We can see all the music been named as track1, track2... the CDs named as CD1, CD2...

Is there any chance to name them as their real name?

Well, you can rename them manually by the FileExplorer mentioned above.

And, there is a automatic way for some CDs:

1, After your phone's Wi-Fi connected to CDRip, run run internet explorer (Chrome, Safari..etc), type the address 43.44.45.46, then enter:

Input Password: admin then press "Login"



First, we get the CDRip access to internet by WiFi Press Network—Wireless:

	③ 4	3.44.45.46	Û
System 👻	Network -	Register -	AUTO REFRESH ON
Systen	Wireless Firewall		

Here you can configure the basic aspects of your device like its hostname or the timezone.

General Settings

Press Scan:



Wireless Overview



Choose your Wi-Fi and Join Network



Join Network: Wireless Scan

34%	hidden Channel: 1 Mode: Master BSSID: 34:96:72:CE:78:15 Encryption: mixed WPA/WPA2 - PSK	Join Network
42%	cwxy22222 Channel: 1 Mode: Master BSSID: BC:5F:F6:25:9A:41 Encryption: mixed WPA/WPA2 - PSK	Join Network
4 65%	hidden Channel: 1 Mode: Master BSSID: 8C:BE:BE:2B:01:1C Encryption: mixed WPA/WPA2 - PSK	Join Network
4 85%	LieBaoWiFi616 Channel: 10 Mode: Master	Join Network

Input Password (of your Wi-Fi) and press "Submit"



Make sure the ESSID is same as your WiFi then press "Save&Apply":

Note: be careful about the "space" at the end of your input, make sure no any space character in front of cursor, otherwise may connect failed (Essid wrong)

	NSAVED CHANGES: 10 AUTO REFRESH ON
ESSID	YourWiFi
Mode	Client
BSSID	34:96:72:CE:78:15
Network	lan: 🕎 🌚
	wan: 🕎
	wan6: 🕎
	wwan:
	create:
	Choose the network(s) you want to attach to this wireless interface or fill out the <i>create</i> field to define a new network.
Ba	ack to Overview
	Save & Apply Save Reset

Make sure click this "Save & Apply" button, *NOT* the "go" button of your mobile's input keyboard

CDRip will restart network, after a few seconds, re-enter to the manager page (you may need reconnect CDRip WiFi).

Press Register—Register:



Press "Register", after a few seconds, you can see

"Done! Register Successfully, or "already registered"

Then register finished



You can choose your Timezone, then "Sync with browser" to set your local time:



System

Here you can configure the basic aspects of your device like its hostname or the timezone.

General Settings	
Local Time	Tue Jul 16 15:54:57 2019 Sync with browser
Hostname	CDRip
Timezone	Asia/Hong Kong

Ok, now we get the CDRip connected to internet, and get registered, now we convert the CD again (by press convert button as step 5), we may find the CD will be automatically named:



And you may also find that not all of CDs can be automatically named, why?

Because to automatically name the CD, the CDRip need to search on the online Database to find the information of it, it can't name it if the CD is not in the Database)

Trouble Shooting:



There is a LED indicator here, normally be green.

Sometimes, this LED show RED color when you press the converter button, and same time the all LEDs on top flash, means there is no USB flash drive and CD in the drive.



If the bottom 3 LEDs flash, means there is no CD or the disk is not a music CD in the drive.



If the Up 3 LEDs flash, means there is no USB flash drive connected, or there is no enough space left of the USB flash drive.



RESET



Press button in this hole with a needle and hold more than 2 seconds then release, CDRip will be reset.

Note: After reset, you have to reconnect CDRip to your Wi-Fi.

Upgrade

If you get a new firmware from CDRip supplier, copy it to a USB flash drive, connect it to CDRip, then short press (less than 2 seconds) button in this hole with a needle, CDRip will be upgrade and reboot, you can see the green indicator flash during upgrade.